

# PX8000 230/115V #AVR HUK

ENGINEERED FOR PROFESSIONAL PERFORMANCE



Ready to move where power is needed, and configured with a strong and compact frame with integrated handle and wheels, that allow to transport it easily.

## Main Features

Frequency	Hz	50
Voltage	V	230
Power factor	cos $\phi$	0.9
Phase and connection		1

## Power Rating

Standby power LTP	kVA	6.0
Standby power LTP	kW	5.4
Continuous power COP	kVA	5.0
Continuous power COP	kW	4.5

### Ratings definition (According to standard ISO8528 1:2005)

**COP** - Continuous Power: It is defined as being the maximum power which a generating set is capable of delivering continuously for an unlimited number of hours, with the maintenance intervals and procedures being carried out as prescribed by the manufacturers.

**LTP** - Limited-Time running Power: It is defined as the maximum power available, under the agreed operating conditions, for which the generating set is capable of delivering for up to 500 h of operation per year (whose no more than 300 for continuative use) with the maintenance intervals and procedures being carried out as prescribed by the manufacturers. No overload capability is available.

### Engine specifications

Engine manufacturer	PRAMAC	
Model	AP190F	
Engine cooling system	Air	
Displacement	cm <sup>3</sup>	420
Aspiration	Natural	
Operating Speed-Nominal	rpm	3000
Speed governor	Mechanical	
Fuel	Petrol	
Oil capacity	l	1.1
Starting system	Electric	



### Alternator Specifications

Class	F	
IP protection	23/44	
Poles	2	
Frequency	Hz	50
Voltage regulation system	Electronic	
Standard AVR	√	



### Dimensional data

Length	(L) mm	727
Width	(W) mm	515
Height	(H) mm	670
Dry weight	Kg	94.5
Fuel tank capacity	l	27



### Autonomy

Fuel consumption @ 75% PRP	l/h	2.00
Fuel consumption @ 100% PRP	l/h	2.66
Running time @ 75% PRP	h	13.50
Running time @ 100% PRP	h	10.15



### Noise level

Guaranteed noise level (LWA)	dB(A)	97
Noise pressure level @ 7 mt	dB(A)	69

## GENSET CONTROL PANELS

Mounted on the genset and complete of: instrumentation, control, protection of the generating set and sockets.

### COMMANDS

- Selector switch: OFF - ON
- Voltage switch 115/230V

### INSTRUMENTATION

- Voltmeter
- Frequency meter
- Hourmeter
- Fuel gauge
- Quick start Guide

### PROTECTIONS

- Thermal protection
- Oil Guard

### SOCKET TYPE

2P+T CEE 115V 32A IP44	1
2P+T CEE 230V 32A IP44	1

