SIEMENS

Data sheet 3RT1036-1BB40



Power contactor, AC-3 50 A, 22 kW / 400 V 24 V DC, 3-pole, Size S2, screw terminal ! Phased-out product! Successor is SIRIUS 3RT2 Preferred successor type is >>3RT2036-1KB40<<

product brand name	SIRIUS
product designation	power contactor
General technical data	
size of contactor	S2
insulation voltage rated value	690 V
degree of pollution	3
surge voltage resistance rated value	6 kV
maximum permissible voltage for safe isolation between coil and main contacts acc. to EN 60947-1	400 V
protection class IP	
on the front	IP20
of the terminal	IP00
shock resistance at rectangular impulse	
• at DC	10g / 5 ms, 5g / 10 ms
shock resistance with sine pulse	
• at DC	15g / 5 ms, 8g / 10 ms
mechanical service life (switching cycles)	
of contactor typical	10 000 000
 of the contactor with added electronically optimized auxiliary switch block typical 	5 000 000
 of the contactor with added auxiliary switch block typical 	10 000 000
reference code acc. to IEC 81346-2	Q
Substance Prohibitance (Date)	01.05.2012 00:00:00
Ambient conditions	
installation altitude at height above sea level maximum	2 000 m
ambient temperature	
during operation	-25 +60 °C
 during storage 	-55 +80 °C
Main circuit	
number of poles for main current circuit	3
number of NO contacts for main contacts	3
number of NC contacts for main contacts	0
operational current	
 at AC-1 at 400 V at ambient temperature 40 °C rated value 	60 A
• at AC-1	
 up to 690 V at ambient temperature 40 °C rated value 	60 A
 up to 690 V at ambient temperature 60 °C rated value 	55 A

-1.40.0	
• at AC-3	50.4
— at 400 V rated value	50 A
— at 690 V rated value	24 A
at AC-4 at 400 V rated value connectable conductor cross-section in main circuit	41 A
at AC-1	
at 60 °C minimum permissible	16 mm²
at 40 °C minimum permissible	16 mm²
operational current for approx. 200000 operating	
cycles at AC-4	
• at 400 V rated value	24 A
at 690 V rated value	12.6 A
operational current	
• at 1 current path at DC-1	
— at 24 V rated value	55 A
— at 110 V rated value	4.5 A
• with 2 current paths in series at DC-1	
— at 24 V rated value	55 A
— at 110 V rated value	25 A
with 3 current paths in series at DC-1	FF A
— at 24 V rated value	55 A
— at 110 V rated value	55 A
operational current	
• at 1 current path at DC-3 at DC-5	25 A
— at 24 V rated value	35 A 2.5 A
 — at 110 V rated value with 2 current paths in series at DC-3 at DC-5 	2.3 A
— at 24 V rated value	55 A
— at 24 V rated value — at 110 V rated value	25 A
 with 3 current paths in series at DC-3 at DC-5 	2071
— at 24 V rated value	55 A
— at 24 V rated value — at 110 V rated value	55 A
operating power	
• at AC-1	
— at 230 V at 60 °C rated value	22 kW
— at 400 V rated value	38 kW
— at 690 V rated value	66 kW
— at 690 V at 60 °C rated value	66 kW
• at AC-2 at 400 V rated value	22 kW
• at AC-3	
— at 230 V rated value	15 kW
— at 400 V rated value	22 kW
— at 500 V rated value	30 kW
— at 690 V rated value	22 kW
operating power for approx. 200000 operating cycles at AC-4	
at 400 V rated value	12.6 kW
at 690 V rated value at 690 V rated value	11.4 kW
thermal short-time current limited to 10 s	400 A
no-load switching frequency	
• at DC	1 500 1/h
operating frequency	
at AC-1 maximum	1 000 1/h
• at AC-2 maximum	400 1/h
• at AC-3 maximum	800 1/h
• at AC-4 maximum	300 1/h
Control circuit/ Control	
type of voltage of the control supply voltage	DC
control supply voltage at DC	
rated value	24 V
operating range factor control supply voltage rated	

value of magnet coil at DC	
initial value	0.8
full-scale value	1.1
closing power of magnet coil at DC	13.3 W
holding power of magnet coil at DC	13.3 W
closing delay	
• at DC	60 100 ms
opening delay	
• at DC	20 25 ms
arcing time	10 15 ms
Auxiliary circuit	
number of NC contacts for auxiliary contacts	0
instantaneous contact	
number of NO contacts for auxiliary contacts instantaneous contact	0
operational current at AC-12 maximum	10 A
operational current at AC-15	
 at 230 V rated value 	6 A
• at 400 V rated value	3 A
operational current at DC-12	
at 60 V rated value	6 A
• at 110 V rated value	3 A
at 220 V rated value	1 A
operational current at DC-13	
at 24 V rated value	10 A
at 60 V rated value	2 A
● at 110 V rated value	1 A
• at 220 V rated value	0.3 A
contact reliability of auxiliary contacts	1 faulty switching per 100 million (17 V, 1 mA)
UL/CSA ratings	
contact rating of auxiliary contacts according to UL	A600 / Q600
contact rating of auxiliary contacts according to UL Short-circuit protection	A600 / Q600
Short-circuit protection	A600 / Q600
Short-circuit protection design of the fuse link	A600 / Q600
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit	
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required	fuse gL/gG: 160 A
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required	fuse gL/gG: 160 A fuse gL/gG: 80 A
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required	fuse gL/gG: 160 A
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch	fuse gL/gG: 160 A fuse gL/gG: 80 A
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required	fuse gL/gG: 160 A fuse gL/gG: 80 A fuse gL/gG: 10 A screw and snap-on mounting onto 35 mm standard mounting rail
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions fastening method	fuse gL/gG: 160 A fuse gL/gG: 80 A fuse gL/gG: 10 A screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions	fuse gL/gG: 160 A fuse gL/gG: 80 A fuse gL/gG: 10 A screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions fastening method • side-by-side mounting height	fuse gL/gG: 160 A fuse gL/gG: 80 A fuse gL/gG: 10 A screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions fastening method • side-by-side mounting	fuse gL/gG: 160 A fuse gL/gG: 80 A fuse gL/gG: 10 A screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes 112 mm 55 mm
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions fastening method • side-by-side mounting height width depth	fuse gL/gG: 160 A fuse gL/gG: 80 A fuse gL/gG: 10 A screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes 112 mm
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions fastening method • side-by-side mounting height width depth required spacing for grounded parts at the side	fuse gL/gG: 160 A fuse gL/gG: 80 A fuse gL/gG: 10 A screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes 112 mm 55 mm
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions fastening method • side-by-side mounting height width depth	fuse gL/gG: 160 A fuse gL/gG: 80 A fuse gL/gG: 10 A screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes 112 mm 55 mm 130 mm
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions fastening method • side-by-side mounting height width depth required spacing for grounded parts at the side	fuse gL/gG: 160 A fuse gL/gG: 80 A fuse gL/gG: 10 A screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes 112 mm 55 mm 130 mm
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions fastening method • side-by-side mounting height width depth required spacing for grounded parts at the side Connections/ Terminals	fuse gL/gG: 160 A fuse gL/gG: 80 A fuse gL/gG: 10 A screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes 112 mm 55 mm 130 mm
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions fastening method • side-by-side mounting height width depth required spacing for grounded parts at the side Connections/ Terminals type of electrical connection	fuse gL/gG: 160 A fuse gL/gG: 80 A fuse gL/gG: 10 A screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes 112 mm 55 mm 130 mm 6 mm
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions fastening method • side-by-side mounting height width depth required spacing for grounded parts at the side Connections/ Terminals type of electrical connection • for main current circuit	fuse gL/gG: 160 A fuse gL/gG: 80 A fuse gL/gG: 10 A screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes 112 mm 55 mm 130 mm 6 mm
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions fastening method • side-by-side mounting height width depth required spacing for grounded parts at the side Connections/ Terminals type of electrical connection • for main current circuit • for auxiliary and control circuit	fuse gL/gG: 160 A fuse gL/gG: 80 A fuse gL/gG: 10 A screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes 112 mm 55 mm 130 mm 6 mm
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions fastening method • side-by-side mounting height width depth required spacing for grounded parts at the side Connections/ Terminals type of electrical connection • for main current circuit • for auxiliary and control circuit type of connectable conductor cross-sections	fuse gL/gG: 160 A fuse gL/gG: 80 A fuse gL/gG: 10 A screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes 112 mm 55 mm 130 mm 6 mm
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions fastening method • side-by-side mounting height width depth required spacing for grounded parts at the side Connections/ Terminals type of electrical connection • for main current circuit • for auxiliary and control circuit type of connectable conductor cross-sections • for main contacts	fuse gL/gG: 160 A fuse gL/gG: 80 A fuse gL/gG: 10 A screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes 112 mm 55 mm 130 mm 6 mm screw-type terminals screw-type terminals
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions fastening method • side-by-side mounting height width depth required spacing for grounded parts at the side Connections/ Terminals type of electrical connection • for main current circuit • for auxiliary and control circuit type of connectable conductor cross-sections • for main contacts — solid	fuse gL/gG: 160 A fuse gL/gG: 80 A fuse gL/gG: 10 A screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes 112 mm 55 mm 130 mm 6 mm screw-type terminals screw-type terminals
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions fastening method • side-by-side mounting height width depth required spacing for grounded parts at the side Connections/ Terminals type of electrical connection • for main current circuit • for auxiliary and control circuit type of connectable conductor cross-sections • for main contacts — solid — stranded	fuse gL/gG: 160 A fuse gL/gG: 80 A fuse gL/gG: 10 A screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes 112 mm 55 mm 130 mm 6 mm screw-type terminals screw-type terminals $2x (0.75 16 mm^2)$ $2x (0.75 25 mm^2)$
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions fastening method • side-by-side mounting height width depth required spacing for grounded parts at the side Connections/ Terminals type of electrical connection • for main current circuit • for auxiliary and control circuit type of connectable conductor cross-sections • for main contacts — solid — stranded — solid or stranded	fuse gL/gG: 160 A fuse gL/gG: 80 A fuse gL/gG: 10 A screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes 112 mm 55 mm 130 mm 6 mm screw-type terminals screw-type terminals 2x (0.75 16 mm²) 2x (0.75 25 mm²) 2x (0,75 16 mm²)
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions fastening method • side-by-side mounting height width depth required spacing for grounded parts at the side Connections/ Terminals type of electrical connection • for main current circuit • for auxiliary and control circuit type of connectable conductor cross-sections • for main contacts — solid — stranded — solid or stranded — finely stranded with core end processing	fuse gL/gG: 160 A fuse gL/gG: 80 A fuse gL/gG: 10 A screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes 112 mm 55 mm 130 mm 6 mm screw-type terminals screw-type terminals 2x (0.75 16 mm²)
design of the fuse link	fuse gL/gG: 160 A fuse gL/gG: 80 A fuse gL/gG: 10 A screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes 112 mm 55 mm 130 mm 6 mm screw-type terminals screw-type terminals 2x (0.75 16 mm²) 2x (0.75 16 mm²) 2x (0.75 16 mm²) 2x (0.75 16 mm²)
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions fastening method • side-by-side mounting height width depth required spacing for grounded parts at the side Connections/ Terminals type of electrical connection • for main current circuit • for auxiliary and control circuit type of connectable conductor cross-sections • for main contacts — solid — stranded — solid or stranded — finely stranded with core end processing — finely stranded without core end processing	fuse gL/gG: 160 A fuse gL/gG: 80 A fuse gL/gG: 10 A screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022 Yes 112 mm 55 mm 130 mm 6 mm screw-type terminals screw-type terminals 2x (0.75 16 mm²)

- solid

— finely stranded with core end processing

at AWG cables for auxiliary contacts

 $2x\ (0.5\ ...\ 1.5\ mm^2),\ 2x\ (0.75\ ...\ 2.5\ mm^2),\ max.\ 2x\ (0.75\ ...\ 4\ mm^2)$

2x (0.5 ... 1.5 mm²), 2x (0.75 ... 2.5 mm²) 2x (20 ... 16), 2x (18 ... 14), 1x 12

Certificates/ approvals

General Product Approval

EMC













Test Certificates

Marine / Shipping

Special Test Certificate

Miscellaneous

Type Test Certificates/Test Report

Miscellaneous





Marine / Shipping

other







<u>Miscellaneous</u>

Confirmation

Miscellaneous

Railway

Special Test Certificate

Further information

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RT1036-1BB40

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RT1036-1BB40

 ${\bf Service \& Support~(Manuals,~Certificates,~Characteristics,~FAQs,...)}$

https://support.industry.siemens.com/cs/ww/en/ps/3RT1036-1BB40

 $Image\ database\ (product\ images,\ 2D\ dimension\ drawings,\ 3D\ models,\ device\ circuit\ diagrams,\ EPLAN\ macros,\ ...)$


 $\underline{\text{http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3RT1036-1BB40\&lang=en}}$


Characteristic: Tripping characteristics, I²t, Let-through current

https://support.industry.siemens.com/cs/ww/en/ps/3RT1036-1BB40/char

Further characteristics (e.g. electrical endurance, switching frequency)

http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RT1036-1BB40&objecttype=14&gridview=view1





last modified: 1/18/2021 🖸