



CS7010 Routine Maintenance Chart

CAUTION: *Do not pressure-wash the operator control panel, fuse panel, contactor panel or engine compartment area.*

Maintenance Item	Interval								
	Day	Wk	Mo	15-20 Hrs	150 Hrs	400 Hrs	1000 Hrs	1500 Hrs	2000 Hrs
Charge battery (battery models)	X								
Check parking brake	X								
Check engine oil (engine models only)	X								
Check engine coolant level (engine models only)	X								
Check air filter service indicator	X								
Clean main and side brooms	X								
Check and clean the scrub brushes	X								
Drain / Check / Clean Tanks & Hoses	X								
Clean recovery tank Debris Basket (51)	X								
Check / Clean / Adjust the squeegee	X								
Clean the hopper	X								
Clean / Inspect scrub deck side skirts	X								
Check/Clean/Rinse vacuum motor foam filter and screen	X								
Check hydraulic oil level		X							



CS7010 Routine Maintenance Chart

Maintenance Item	Interval								
	Day	Wk	Mo	15-20 Hrs	150 Hrs	400 Hrs	1000 Hrs	1500 Hrs	2000 Hrs
Lubricate squeegee caster wheels and pivot			X						
Lubricate steering gears			X						
Lubricate squeegee side wheels			X						
Lubricate engine/battery bay latch			X						
Lubricate recovery tank latch			X						
Lubricate brake linkage			X						
Check the electrolyte level in the battery (battery models)				X					
Check the battery cables and connections				X					
Rotate main broom				X					
Inspect and clean solution filter				X					
Rotate the scrub brushes				X					
Inspect/adjust main and side brooms				X					
Clean the DustGuard system spray nozzles				X					
Inspect broom housing skirts				X					
Check / Clean Hopper Dust Control Filter				X					
Inspect hopper seals				X					



CS7010 Routine Maintenance Chart

Purge Detergent System (EcoFlex only)				X					
Clean radiator					X				
Perform general engine maintenance					X				
Change engine oil and filter					X				
Inspect and drain any oil buildup from the LP fuel EPR					X				
Inspect complete air intake system (engine models only)						X			
Check engine battery electrolyte level & terminals						X			
Replace fuel filter (engine models only)						X			
Change the spark plugs (LP and petrol only)							X		
Flush the radiator							X		
Replace Alternator Drive Belt							X		
Check vacuum motor carbon brushes (1200 hrs)							X		
Check main broom motor carbon brushes								X	
Check side broom motor carbon brushes								X	
Replace vacuum motor									X
Check scrub brush motor carbon brushes									X
Perform engine maintenance									X